



9





the remote controller, and the LED indicator "flashes once again" means the pairing is cuccessful.

Please refer to the user manual of remote controllers for detailed instruction and use. (1) The RM2.4G remote controller can learn multiple

10

he two buttons at the bottom named 'All ON' and 'All OFF' allow you to turn on or off all the buttons above and they cannot learn any other functions. You can also purchase our eWeLink-Remote Smar Switch (1/2/3 gang single live wire) as needed. 11

11

Pairing with eWeLink APP



Download APP




2 Add the 2.4G remote controller on eWeLink



12

Tap "+" and seledt "2.4G Remote", then select

3 Pairing with APP



Long press the pairing button on the device for 10s until the LED indicator"fl ashes once" and release. Then tap the remote controller button on APP,and the LED indicator "flashes once again" means that the pairing is succeul.

 The device can add 4 2.4G remote controllers at most(include APP button and RM2.4G remote controller), and the fifth remote controller data will automatically cover the first one.

Clearing RM2.4G remote controller



Long press the pairing button on the device for 5s until the LED indicator "flashes twice" and release button and RM2.4G remote controller) are cleared successfully. 13

Specifications

Name Smart Switch Input AC 100-240V 50/60Hz 10A Max Output AC 100-240V 50/60Hz 10A Max Operating Systems (Android 4.1 & iOS 9.0) or higher Frequence 2 4GHz Standard Over 40M (Open space) Distance Material Dimension 57*40*20mm

Features

This device is a 2.4GHz smart switch that supports You can also create schedules and scenes in the app...
It works with eWeLink 2.4GHz gateway for remote control and voice control

14





eWeLink has integrated with mainstream Al platforms. To ensure users can know quickly which platforms/smart speakers are compatible with products, manufacturers can print the poster version with "Works with Al"of eWeLink logo and attach it in the package with the user manual.



(!) Smart products supporting eWeLink APP need get the certification of the corresponding platform before using the logo of Al voice platforms. Please refer to the product certification to make a deletion if manufacturers use the version on the package

15